

Flash functions available with cameras when used with an external Speedlight

Z 7II, Z 7, Z 6II, Z 6, Z 5, Z 9, Z 8, Z 6III

			Speedlight compatible with CLS										Speedlight incompatible with CLS								
			SB-5000	SB-900 SB-910	SB-800	SB-700	SB-600	SB-500	SU-800		SB-R200	SB-400	SB-300	SB-80DX SB-28DX	SB-50DX	SB-28 SB-25 SB-24	SB-30, SB-27 SB-22S, SB-22	SB-23 SB-21B SB-29S	SB-12 SB-21A + AS-6	SB-16A SB-17 + AS-6	
										Commander	Close up										
Single flash	i-TTL	i-TTL balanced fill-flash *1	○	○	○	○	○	○	-	-	-	○	○	-	-	-	-	-	-	-	
		Standard i-TTL	○*2	○*2	○*2	○	○*2	○	-	-	-	○	○	-	-	-	-	-	-	-	
		TTL flash control for Speedlights incompatible with CLS	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		AA Auto aperture flash	○*5	○*3	○*3	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		A Non-TTL auto flash	○*5	○*3	○*3	-	-	-	-	-	-	-	-	-	○	-	○	○	-	-	○
		GN Distance-priority manual flash	○	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		M Manual flash	○	○	○	○	○	○	○*4	-	-	-	○*4	○*4	○	○	○	○	○	○	○
		RPT Repeating flash	○	○	○	○	-	-	-	-	-	-	-	-	○	-	○	-	-	-	-
Optical AWL	Master	Commander function	○	○	○	○	-	○*4	○	○	-	-	-	-	-	-	-	-	-	-	
		Controllable group	A/B/C	A/B/C	A/B/C	A/B	-	A/B	A/B/C	A/B/C	-	-	-	-	-	-	-	-	-	-	
		Mode setting	A/B/C	A/B/C	A/B/C	A/B	-	A/B	A/B/C	A/B/C	-	-	-	-	-	-	-	-	-	-	
		Mode setting for remote	Same as master	Same as master	Same as master	Same as master	-	Master+AA	Same as SB-800	Same as SB-700	-	-	-	-	-	-	-	-	-	-	
	Remote	i-TTL	i-TTL flash control	○	○	○	○	-	○*4	-	-	-	-	-	-	-	-	-	-	-	
		[A,B]	Quick wireless control	○	-	-	-	-	-	-	○	-	-	-	-	-	-	-	-	-	
		AA	Auto aperture flash	○*5	○*5	○*5	-	-	○*4	-	-	-	-	-	-	-	-	-	-	-	
		A	Non-TTL auto flash	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
		M	Manual flash	○	○	○	○	-	○*4	-	-	-	-	-	-	-	-	-	-	-	
		RPT	Repeating flash	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	
		i-TTL	i-TTL flash control	○	○	○	○	○	○	-	-	○	-	-	-	-	-	-	-	-	
		[A,B]	Quick wireless control	○	○	○	○	○	○	-	-	○	-	-	-	-	-	-	-	-	
	Radio-control led AWL	Remote	AA	Auto aperture flash	○*5	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
			A	Non-TTL auto flash	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
			M	Manual flash	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
			RPT	Repeating flash	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Color Information Communication (flash)			○	○	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-		
Color Information Communication (LED light)			-	-	-	-	-	○	-	-	-	○	-	-	-	-	-	-	-		
Auto FP high-speed sync *6			○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○		
EV lock *7			○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○		
AF-assist for multi-area AF			-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
Modeling illumination using camera control			○	○	○	○	○	○	Signal only	-	Remote only	-	-	-	-	-	-	-	-		
Modeling illumination using flash control			○	○	○	-	-	-	Signal only	-	Remote only	-	-	-	-	-	-	-	-		
Red-eye reduction			○	○	○	○	○	○	-	-	-	○	-	-	-	-	-	-	-		
Unified flash control			○	-	-	-	-	-	○	-	-	○	○	-	-	-	-	-	-		
Flash mode setting from camera			○	-	-	-	-	-	-	-	-	○	○	-	-	-	-	-	-		
Scenes/special effects flash control			○	-	-	-	-	-	○	-	-	-	○	○	-	-	-	-	-		
Test firing from camera			○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
Flash unit firmware update via camera			○	○	-	-	○	-	○	-	-	-	-	-	-	-	-	-	-		
SU-4	Master	AA	Auto aperture flash	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
		A	Non-TTL auto flash	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-		
		GN	Distance-priority manual flash	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-		
		M	Manual	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-		
	Remote	AUTO	Auto	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-		
		M	Manual	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-		

*1 Not available with spot metering.

*2 Can be also selected with flash unit.

*3 AA/Mode A selection preformed on flash unit using custom settings. Mode A will be selected when a non-CPU lens is used.

*4 Can only be selected using camera Flash Control option.

*5 Auto aperture flash mode and non-TTL auto flash mode cannot be selected in the flash unit's custom menu.

Non-TTL auto flash mode will be applied if a non-CPU lens is used without specifying the lens' maximum aperture using **Non-CPU lens data** in the camera's setup menu.

*6 Available only in i-TTL, AA, A, GN and M.

*7 Available only in i-TTL, AA and A.

Cannot be configured	—	Not supported by camera
	Text entered	Not supported by camera, but flash functions are indicated
Can be configured	—	Function not available with flash unit
	○	Available
Text entered	○	Available; additional information noted