

■ Flash functions available with cameras when used with an external Speedlight

F6

			Speedlight compatible with CLS										Speedlight incompatible with CLS								
			SB-5000	SB-900 SB-910	SB-800	SB-700	SB-600	SB-500	SU-800		SB-R200	SB-400	SB-300	SB-80DX SB-28DX	SB-50DX	SB-28 SB-26 SB-25 SB-24	SB-30, SB-27 SB-22S, SB-22 SB-20, SB-16B SB-15	SB-23 SB-29 SB-21B SB-29S	SB-12 SB-21A + AS-6	SB-16A SB-17 + AS-6	
										Commander	Close up										
Single flash	i-TTL	i-TTL balanced fill-flash *1	○	○	○	○	○	○	○	-	-	-	○	○	-	-	-	-	-	-	-
		Standard i-TTL	○*2	○*2	○*2	○	○*2	○	-	-	-	○	○	-	-	-	-	-	-	-	-
	TTL	3D multi-sensor balanced fill-flash *1 *8	-	-	-	-	-	-	-	-	-	-	-	○	○	-	-	-	-	-	-
		Multi-sensor balanced fill-flash *1 *9	-	-	-	-	-	-	-	-	-	-	-	○	○	-	-	-	-	-	-
	AA	Standard TTL flash	-	-	-	-	-	-	-	-	-	-	-	○	○	-	-	-	-	-	-
		Auto aperture flash	○*3	○*3	○*3	-	-	-	-	-	-	-	-	○	○	-	-	-	-	-	-
		Non-TTL auto flash	○*3	○*3	○*3	-	-	-	-	-	-	-	-	○	-	○	-	-	-	-	○
		Distance-priority manual flash	○	○	○	○	-	-	-	-	-	-	-	○	-	○	-	-	-	-	○
		Manual flash	○	○	○	○	○	-	-	-	-	-	-	○	○	○	○	○	○	○	○
		Repeating flash	○	○	○	-	-	-	-	-	-	-	-	○	-	○	-	-	-	-	-
Commander function		○	○	○	-	-	-	-	○	○	-	-	-	-	-	-	-	-	-	-	
Controllable group		A/B/C	A/B/C	A/B/C	A/B	-	A/B	A/B/C	A/B(C)	-	-	-	-	-	-	-	-	-	-	-	
Optical AWL	Master	Setting	A/B/C	A/B/C	A/B/C	A/B	-	A/B	A/B/C	A/B(C)	-	-	-	-	-	-	-	-	-	-	
		Mode setting	Individual	Individual	Individual	Common	-	Individual	Individual	Individual	-	-	-	-	-	-	-	-	-	-	
		Mode setting for remote	Same as master	Same as master	Same as master	Same as master	-	Master+AA	Same as SB-800	Same as SB-700	-	-	-	-	-	-	-	-	-	-	
		i-TTL	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		[A:B] Quick wireless control	○	○	○	○	-	-	-	○	-	-	-	-	-	-	-	-	-	-	-
	Remote	AA	○*5	○*5	○*5	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		A	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		M	○	○	○	○	-	-	-	-	-	-	-	○	-	-	-	-	-	-	-
		RPT	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
		i-TTL	○	○	○	○	○	○	○	-	-	○	-	-	-	-	-	-	-	-	-
[A:B] Quick wireless control	○	○	○	○	○	○	○	-	-	○	-	-	-	-	-	-	-	-	-		
AA	○*5	○*5	○*5	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
A	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
M	○	○	○	○	○	○	-	-	-	○	-	-	-	-	-	-	-	-	-		
RPT	○	○	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-		
Color Information Communication (flash)			-	-	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
Color Information Communication (LED light)			-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
Auto FP high-speed sync *6			○	○	○	○	○	○	○	○	-	-	-	-	-	-	-	-	-	-	
EV lock *7			○	○	○	○	○	○	○	○	○	○	-	-	-	-	-	-	-	-	
AF-assist for multi-area AF			○	○	○	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	
Red-eye reduction			○	○	○	○	○	○	-	-	-	○	-	○	?	?	?	?	?	?	
Modeling illumination using flash control			○	○	○	-	-	-	Signal only	-	Remote only	-	-	-	-	-	-	-	-	-	
Modeling illumination using camera control			○	○	○	○	○	○	Signal only	-	Remote only	-	-	-	-	-	-	-	-	-	
Unified flash control			-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
Flash mode setting from camera			-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
Scenes/special effects flash control			-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
Flash unit firmware update via camera			-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
SU-4	Master	AA	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
		A	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
		GN	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
		M	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Remote	AUTO	○	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	
		M	○	○	○	○	○	-	-	-	-	-	-	-	-	-	-	-	-	-	

\*1 Not available with spot metering.  
 \*2 Can be also selected with flash unit.  
 \*3 AA/Mode A selection performed on flash unit using custom settings. Mode A will be selected when a non-CPU lens is used.  
 \*4 Can only be selected using camera Flash Control option.  
 \*5 Auto aperture flash mode and non-TTL auto flash mode cannot be selected in the flash unit's custom menu.  
 Non-TTL auto flash mode will be applied if a non-CPU lens is used without specifying the lens' maximum aperture using **Non-CPU lens data** in the camera's setup menu.  
 \*6 Available only in i-TTL, AA, A, GN and M mode.  
 \*7 Available only in i-TTL, AA and A.  
 \*8 Available only with a type G or D CPU lens  
 \*9 Available only with a non-CPU lens or a CPU lens other than type G or D

Cannot be configured	---	Not supported by camera
	Text entered	Not supported by camera, but flash functions are indicated
Can be configured	---	Function not available with flash unit
	○	Available
Text entered	Available; additional information noted	