

Additional information: CLS-compatible cameras/built-in flash functions

				D-SLR							M.	A-CIL	C-DSC								
				D7500	D810A D800E D750	D610 D300S D700	D7200 D7100 D7000 D90 D80	D200	D70 D70S	D50	D5600 D5500 D5300 D5200 D5100 D5000	D3400 D3300 D3200 D3100 D3000	D60 D40 D40X	Z 50	V3 V2 V1	A	P7800 P7700	P7100 P7000	P6000	P1000 P5100 P5000 P950 E8800 E8700 E8400	
CLS function	Single flash	i-TTL	i-TTL balanced fill-flash *1	○	○	○	○	○	○	○	○	○	Standard i-TTL only *	-	○	-	-	-	-		
			Standard i-TTL	○	○	○	○	○	○	○	○	○	○	○	○	○	○				
			M	Manual	○	○	○	○	○	○	○	○	○	○	○	○	○				
		Optical AWL	Master	RPT	Repeating flash	○	○	-	-	-	-	-	-	-	○	○	○	○	-	-	
	Setting			Commander	○	○	○	○	-	-	-	-	-	-	○	○	○	○	-	-	
				Controllable group	M/A/B	M/A/B	M/A/B	Group A only	-	-	-	-	-	-	M/A	-	-	-	-		
				Controllable channel	1 - 4	1 - 4	1 - 4	3	-	-	-	-	-	-	3	-	-	-	-		
	Remote		i-TTL	i-TTL flash control	○	○	○	-	-	-	-	-	-	-	○	○	○	○	-	-	
			M	Manual	○	○	○	-	-	-	-	-	-	-	○	○	○	○	-	-	
			i-TTL	i-TTL flash control	○	○	○	○	-	-	-	-	-	-	○	○	○	○	-	-	
			AA	Auto aperture flash	○	○	○	○	-	-	-	-	-	-	○	○	○	○	-	-	
			M	Manual	○	○	○	○	-	-	-	-	-	-	○	○	○	○	-	-	
			Radio-controlled AWL	Setting	Radio-controlled AWL	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
					Optical/radio AWL (group setting)	D/E/F	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
				Remote	i-TTL	i-TTL flash control	○	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	[A: B]	Quick wireless control			-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
	AA	Auto aperture	○		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
	A	Non-TTL auto	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
	M	Manual	○		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
	RPT	Repeating flash	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
	Color information communication				-	-	-	-	-	-	-	-	-	-	-	-	-	-			
	Auto FP high-speed sync *2				○	○	○	-	-	-	-	-	-	-	-	-	-	-	-		
	FV lock *3				○	○	○	○	-	-	○	-	○	-	-	-	-	-	-		
	AF-assist for multi-area AF				-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
	Red-eye reduction				-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
	Modeling illumination using camera control				○	○	○	-	-	-	-	-	-	-	-	-	-	-	-		
	Flash mode setting from camera				-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		
	Flash unit firmware update via camera				-	-	-	-	-	-	-	-	-	-	-	-	-	-	-		

*1 Not available with spot metering
*2 Available only when built-in flash is off
*3 i-TTL, AA only
*4 Just "i-TTL" with no distinction between "i-TTL balanced fill-flash" and "standard fill-flash" with A-CIL

-	Not supported by camera
○	Available
Text entered	Available; additional information noted

Cameras not applicable (without a built-in flash)	D6 D5 D4 D4s D3 D3x D3s D2H D2Hs D2X D2Xs D850 D780 D500
	Z 7II Z 7 Z 6II Z 6 Z 5 Z fc
	J5 J4 J3 J2 J1 S2 S1
	AW1
C-DSCs without accessory shoe (so many that individual models are not listed)	